#### ELECTRICAL SPECIFICATIONS Item No. 105.002 / Page 1 / 3 Print Date 13.11.2023 10:45

## **TECHNICAL DATASHEET**

105-3.3

5 Watt, non isolated, single output buck converter

All parameters defined on Ta=25°C, IoNom = 1.5 ADC and UiNom = 24VDC

### **ABSOLUTE MAXIMUM RATINGS**

parameter	unit	typ
Input peak voltage	VDC	38.00

#### THERMAL CHARACTERISTICS

parameter	min to max	typ
Ambient temperature range	-40°C / +85°C	
Max. case temperature for thermal shut down [°C]		+110°C
Storage temperature (device not in operation)	-10°C / +65°C	
Relative maximum humidity under storage		75% RH
Storage under worst conditions [in days]		25

### **SPECIALS**

parameter	unit	conditions	typ
Switching frequency	kHz		200
Efficiency at medium loads	%	0.5loNom	88.00
Efficiency at full loads	%	loNom	87.00
MTTF	h	SN29500 @ 70°	1 800 000

### **COMPLIANCE**

parameter	fulfilled	notes
61000-6-4 (EMC - Emission standard for industrial environment)	<b>✓</b>	
55022 <a< td=""><td><b>✓</b></td><td></td></a<>	<b>✓</b>	

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



# **TECHNICAL DATASHEET**

105-3.3

5 Watt, non isolated, single output buck converter

### **INPUT**

parameter	unit	conditions	min	typ	max
Input voltage range	VDC	loNom	6	24	36
No load input current	mA	UiNom		2	
Max. input current	Α	UiNom		1	
Input start up voltage	VDC	UiNom		3.9	
Undervoltage lockout	VDC	UiNom		3.7	
Input current overshoot during soft start ramp up	%	loNom		130	
Generated AC-ripple on the supply (BW=20MHz)	mVp-p	UiNom/IoNom		60	
Generated HF-noise on the supply (BW=20MHz)	mVp-p	UiNom/IoNom		90	
Typical input noise slew rate (BW=500MHz)	mVp-p	UiNom/IoNom		120	

### **OUTPUT**

parameter	unit	conditions	min typ max
Output voltage	VDC	loNom	3.3
Minimum required load to obtain the specified output voltage	%	UiNom	0
Generated AC-ripple on the output (BW=20MHz)	mVp-p	UiNom/IoNom	25
Generated HF-noise on the output (BW=20MHz)	mVp-p	UiNom/IoNom	20
Typical output noise slew rate (BW=500MHz)	mVp-p	UiNom/IoNom	110
Output voltage accuracy	%	loNom	+/-1.50%
Output voltage overshoot at initial switch-on	%	loNom	overdamped
Rated output power	W		5

## **CONTROL**

parameter	unit	conditions	min	typ	max
Static line regulation	%	loNom/UiMinUiM	ах	0.05	
Static load regulation	%	loMinloMax/UiNo	m	0.1	
Dynamic load change adjusting time	ms	LoadChange 109	0%	0.50	
Dynamic load change deviation to nominal output voltage	٧	LoadChange 109	0%	0.25	
Maximum admissible capacitive load	uF	loNom		6600	
Initial switch on time	ms	loNom		24	
Softstart ramp up time	ms	loNom		12	

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



## **TECHNICAL DATASHEET**

105-3.3

5 Watt, non isolated, single output buck converter

#### **MECHANICAL**


haramerei	unit	
Overall dimensions	mm	32x20x10
Weight	g	14


Pin No.	Function	<b>Electrical Determination</b>
1	Vi+	Input voltage positive
10	Vi-/Vo-	Input and output voltage neg
11	Vo+	Output voltage positive
12	Vi-/Vo-	Input and output voltage neg
13	Vi-/Vo-	Input and output voltage neg
14	Vo+	Output voltage positive
15	Vi-/Vo-	Input and output voltage neg
24	Vi+	Input voltage positive

#### **Mechanical dimensions and Pin configuration**

All dimensions in mm Connector type: THT

Case: Dil24





All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.

